

ORIGINAL - METAL BASE R5W

Original spare part



The cost-effective original spare parts for trucks

Discover OSRAM's ORIGINAL signal lamps with metal bases - high-quality original spare parts for 24 volt lamps. Due to the wide product range, the lamps can be used for different applications: as position and parking lights, indicator, brake, fog and reversing lights as well as number plate and side position lights.

Technical data

Product information

Order reference	5626
Application (Category and Product specific)	Auxiliary lamp


Electrical data

Power input	7 W
Nominal voltage	24.0 V
Nominal wattage	5.00 W
Power input tolerance	±10 %
Test voltage	28.0 V

Photometrical data

Luminous flux	50 lm
Luminous flux tolerance	±25 %

Dimensions & weight



Length	37.5 mm
Diameter	16.0 mm
Product weight	7.00 g

Lifespan

Lifespan B3	80 h
Lifespan Tc	250 h

Additional product data

Base (standard designation)	BA15d
-----------------------------	-------

Product datasheet

Capabilities

Technology	AUX
------------	-----

Certificates & standards

ECE category	R5W
--------------	-----

Country specific categorizations

Order reference	5626
-----------------	------

Country specific information

Product code	METEL code	SEG-No.	STK-Number	UK Org
4008321095336	OSRA5626	-	-	-
4008321095343	OSRA5626	-	-	-
4008321095336	OSRA5626	-	-	-

Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4008321095336	ORIGINAL - METAL BASE R5W	Unpacked 1	25 mm x 15 mm x 15 mm	0.01 dm ³	9.00 g
4008321095343	ORIGINAL - METAL BASE R5W	Folding carton box 10	54 mm x 40 mm x 138 mm	0.30 dm ³	83.00 g
4008321095350	ORIGINAL - METAL BASE R5W	Shipping carton box 50	210 mm x 147 mm x 68 mm	2.10 dm ³	487.00 g

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.



OSRAM