Product datasheet

OSRAM

ORIGINAL - FESTOON -

Original spare part





The cost-effective original spare parts

The ORIGINAL festoon lamps with OSRAM's reliable OEM quality can be used as original spare parts for a wide range of festoon lamps. The typical application areas of the lamps are number plate and side position lights as well as interior lighting and reading lights.

Product datasheet

Technical data

Product information

Order reference	6428	
Application (Category and Product specific)	Auxiliary lamp	

Electrical data

Power input	3.5 W
Nominal voltage	12.0 V
Nominal wattage	3.00 W
Test voltage	13.5 V
Power input tolerance	±10 %

Photometrical data

Luminous flux	29 lm
Luminous flux tolerance	±20 %

Dimensions & weight





Diameter	8 mm
Product weight	1.76 g
Length	28.0 mm

Lifespan

Lifespan B3	600 h
Lifespan Tc	1200 h

Additional product data

Base (standard designation)	SV7-8
base (stanuaru designation)	577-0

Product datasheet

Capabilities

Technology	AUX
Certificates & standards	
ECE category	-
Country specific categorizations	
Order reference	6428

Country specific information

Product code	METEL code	SEG-No.	STK-Number	UK Org
4008321094384	OSRA6428	-	-	-
4008321094391	OSRA6428	-	-	-
4008321094384	OSRA6428	-	-	-

Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4008321094384	ORIGINAL FESTOON 6428	Unpacked 1	50 mm x 13 mm x 18 mm	0.01 dm³	8.40 g
4008321094391	ORIGINAL FESTOON 6428	Folding carton box 10	38 mm x 54 mm x 141 mm	0.29 dm³	31.60 g
4008321094407	ORIGINAL FESTOON 6428	Shipping carton box 50	205 mm x 64 mm x 144 mm	1.89 dm³	208.00 g

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.















